


SAVE THESE INSTRUCTIONS

Current

READ THOROUGHLY BEFORE INSTALLATION



WARNING! Fixtures must be grounded and installed in accordance with the National Electrical Code and all local codes. Failure to do so may increase the **RISK OF PERSONAL INJURY, PROPERTY DAMAGE, FIRE AND DEATH**. Install and use so fixture failures do not cause a hazard and use only in environments for which the product is specifically marked.

WARNING! This product contains chemicals known to the State of California to cause cancer, birth defects, and/or other reproductive harm. Thoroughly wash hands after installing, handling, cleaning, or otherwise touching this product.

WARNING! Dangerous voltage exist within the unit and all precautions usually observed in handling high voltage equipment should be observed when replacing light engine or otherwise servicing luminaires. Disregarding this warning could result in electrical shock and possible injury to the individual installing or servicing this equipment. Installation and servicing should be done by qualified personnel.

CAUTION! Follow ALL luminaire recommendations, product markings, instructions, restrictions and warnings regarding luminaire operation and burning position. Luminaire label shows electrical and environmental requirements and restrictions.

NOTE! This luminaire is designed for outdoor lighting applications with ambient temperatures not exceeding 40°C (104°F).

All electrical work must be done by a qualified electrician.

Turn off electric power to all affected circuits and allow to cool before installation or servicing.

A regularly scheduled maintenance program should be established to retain optimum light output and reduce heat retention. Dusting with a soft, clean, dry cloth is normally sufficient for the optical system. Any accumulation of dust or dirt should be removed regularly.

Carefully read these instructions before installing product. If you do not understand these instructions, before starting any work, contact your Lighting distributor or Lightingtechsupport@currentlighting.com or (864) 678-1000

Give instructions to facility owner/manager for future reference.

I. Mounting The Fixture

Tools Required: **Hardware included:**

Power Drill
M6.3 hexagonal bit
Self tapping Screws (4 pcs) - M6.3x60mm
Safety wire (1 pc)
Screw for safety wire (1 pc) - M5x6mm
Foam Housing Pads (4 pcs)




FIGURE 1

1. Turn off power to electrical connections.

2. Wiring must be performed by a qualified electrician.

Make electrical connections according to the local and National Electrical Codes.

This product is only suitable for 120-277V.

3. Remove fixture from packaging along with hardware bag.

There are 5 wires coming out of this fixture: (Wiring shown on FIGURE 1)

Black Wire - Line Voltage

White Wire - Neutral

Green Wire - Ground

Purple Wire - (V+) DIM Lead (if applicable)

Pink Wire - (V-) DIM Lead (if applicable)

If the dimming leads are not used, cap off each of the these wires.

4A. Ceiling Mount

(1) Attach one side of the safety rope to the light fixture and the other side to the ceiling to secure the light fixture during installation. (FIGURE 2)

(2) Connect the wires as shown in the figure. (FIGURE 1)

(3) Fixed the light fixture to the ceiling with M6.3x60MM self-tapping self-drilling screws. (FIGURE 3)




FIGURE 2




FIGURE 3

93131705 Rev. G

SAVE THESE INSTRUCTIONS

4B. Pendant Mount:

- Attach one side of the safety wire to the fixture and the other side to the ceiling to securely hold the fixture in place during installation (Fig. 4).
- Connect the wires as shown (Fig. 6) and then secure fixture to the ceiling with the 3/4" NPT Pendant (Fig. 5). If the dimming leads are not used, cap off each of the these wires.




FIGURE 4




FIGURE 5




FIGURE 6

NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense. Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

