

NOTE: Components shown in images are representative only and may vary based on the configuration ordered.

**CAUTION! — READ THIS FIRST — IMPORTANT SAFETY INSTRUCTIONS**

**WARNING**

- To reduce the risk of death, personal injury or property damage from fire, electric shock, falling parts, cuts/abrasions, and other hazards read all warnings and instructions included with the fixture box and all fixture labels.
- Before installing, servicing, or performing routine maintenance upon this equipment, follow these general precautions.
- Commercial installation, service and maintenance of luminaires should be performed by a qualified licensed electrician.
- For the installation: If you are unsure about the installation or maintenance of the luminaires, consult a qualified licensed electrician and check your local electrical code.
- To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.
- Do not make or alter any open holes in an enclosure of wiring or electrical components during installation.

**WARNING**

- Turn off electrical power at fuse or circuit breaker box before wiring fixture to the power supply.
- Turn off the power when you perform any maintenance.
- Verify that supply voltage is correct by comparing it with the luminaire label information.
- All wiring connections should be capped with UL approved wire connectors.

**CAUTION**


- Avoid direct eye exposure to the light source while it is on.
- Account for small parts and destroy packing material, as these may be hazardous to children.
- Risk of burn. Disconnect power and allow fixture to cool before handling..

**NOTICE:** Green ground screw provided in proper location. Do not relocate.

**NOTICE:** Minimum 90° supply conductors.


**NOTICE:** Specifications and dimensions subject to change without notice.

**NOTICE:** Suitable for Dry or Damp location.



**INCLUDED MATERIAL**


- A.** End Plates (2pcs)
- B.** Side Plates (2pcs)
- C.** Door Assembly body (1pc)
- D.** Self-tapping screws (4pcs)




**NOTICE:**

The existing fluorescent luminaires housing shall be larger than dimensions described in below drawings:

**2'X2'**



**2'X4'**




## INSTALLATION

### STEP 1

Prior to installation, disconnect all incoming power to fixture. Remove existing hardware (lens/lens frame, parabolic louver, reflectors/ballast covers, brackets, lamps/lamp holders). Leave supply and grounding leads.


NOTE: Follow all federal and local regulations when disposing of lamps and removed components.



### STEP 2


Install LED panel end brackets to each end of the existing fixture by gently lifting it and placing LED panel end brackets between the fixture and T-grid.

If you are not pleased with the gap between the fixture and T-grid, you may install LED panel side brackets between the fixture and T-grid, there are two tabs to allow for placing the side brackets into the slot of end brackets.




### STEP 3

Secure the LED panel brackets to the existing fixture using the provided #8 x 1/2" self-drilling screws.




### STEP 4

Locate the door assembly body onto the keyholes of end brackets, and then slide the door assembly body horizontally to the end of slots.



### STEP 5

Hook the safety cables into the holes positioned the end brackets. Use the provided wire caps to connect the wire leads of the troffer kits to the main power leads (Black–Live, White–Neutral, Green–Grounding).



### STEP 6

Secure the door assembly body by lock the latches riveted on each end of the assembled door frame.

