



RM4 LED Signals Rail

8" (200mm) Wayside Colorlight – 120V AC – 70 Series



BEFORE YOU BEGIN

Read these instructions completely and carefully. If you prefer to have this Installation Instructions document in other languages, visit our official website at: www.LED.com/transportation

⚠ WARNING / AVERTISSEMENT

RISK OF ELECTRIC SHOCK

Disconnect Before Servicing or installing product. The LED module must be installed into a signal head with adequate ingress protection for the location (protection from the weather).

RISQUES DE DÉCHARGES ÉLECTRIQUES

Couper l'alimentation avant le dépannage ou avant l'installation du produit. Le module DEL doit être installé dans une tête de signal avec une protection adéquate d'entrée pour l'emplacement (protection contre les intempéries).

Operating Specifications

Nominal Input Voltage	110V AC
Voltage Range	85 - 135V A C
Nominal Power Consumption	View RAIL340 for reference

Prepare Electrical Wiring



Electrical Requirements

- Follow all National Electric Codes (NEC) and local codes.

Important Information

- Always use a sun shielding apparatus such as a visor or hood over the signals.
- Do not attempt to open the LED module. No assembly is required.
- Relay flashers are the only approved means of flashing the LED signal.
- As per AREMA guidelines, provisions should be made for periodic functional checks of safety devices and features incorporated into this product.
- Current recommends that primary and secondary surge protection be added additional to the tertiary surge protection in the lamp. Arema 11.3.3
- This product is intended solely for the use of rail signaling and is not intended for use in any other application.



This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
CAN ICES-005 (A)/NMB-005(A)

NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

Testing

When testing the lamp before installation, first check the electrical characteristics on the label on the back of the lamp (see **B**) below) to avoid damaging the lamp.

Installation Steps

NOTE: Failure to properly follow these instructions may cause signal to

- ① **Existing signal head in the field:** Remove lens and incandescent bulb assembly from housing.
- ② **Existing in-line rheostat in the field:** Set rheostat (variable resistor) to zero (0) or remove completely.
- ③ **Voltage settings:** Check the label on the side of the LED module **B** to ensure the voltage corresponds to the system voltage.
- ④ **Color-Coded Wiring:** The module wires have been color-coded to identify the color of the signal when it is off. For example, green signals have green wires. **C**
- ⑤ **Insertion of LED module into signal head:** Insert the LED module into lens slot, then rotate until arrow **A** points up. Tighten metal tabs or insert LED module into the external ring holder.

