



KLVL202

**INSTRUCTIONS PERTAINING TO A RISK OF FIRE OR INJURY TO PERSONS
IMPORTANT SAFETY INSTRUCTIONS!**

⚠ WARNING: To reduce the risk of **FIRE OR INJURY TO PERSONS:** Do not overdrive fixtures with greater than 12 volts or fixture over-heating and short lamp life will occur. Do not overload the transformer by installing (or relamping) higher wattage lamps than planned. Note: Total wattage of all lamps connected to one transformer must not exceed the capacity of that transformer. Do not install luminaire within 10 feet (3.04m) of a pool, spa or fountain. **DO NOT** operate luminaire with missing or damaged lens.

⚠ SAFETY WARNING: When relamping, be sure electrical supply is **OFF**. Use discretion when touching fixture and be sure to allow fixture to cool before relamping.

MAINTENANCE: To maintain light efficiency and prevent fixture-overheating, glass lenses and enclosure must be kept clean and free of dirt, dust, leaves, trash (combustible materials) and mineral deposits from water. Particular care should be taken not to locate fixtures where small children can reach them if higher wattages are used.


KEEP THIS SHEET FOR FUTURE REFERENCE.

- Tools Required:** Philips Screwdriver Adjustable Wrench
 1/8" Hex Wrench Silicone Grease

⚠ Make certain the electrical supply is **OFF** before starting fixture installation.



1. Tighten coupling onto mounting device. (See KIM Installation Instructions for Low Voltage Mounting Options, part no. 95488.)



2. Install fixture onto coupling. Attach fixture cable to main system cable with a KLV410 connector.



3. Adjust angle using swivel screw. Retighten after adjustments.




4. Loosen setscrew, adjust fixture rotation, and tighten setscrew. Connect fixture to main system cable with a KLV410 Sealed Connector. (See KLV410 Installation Instructions)

IMPORTANT: Do not overload the transformer by installing higher wattage fixtures than planned. Remember, the total wattage of all fixtures connected to one transformer must not exceed the capacity of that transformer.

IMPORTANT: When fixtures are aimed up, particular care should be taken to keep lens free of debris and mineral deposits. When fixtures are in an area where debris or mineral deposits are likely to be a problem, lower wattage lamps should be used, and lenses should be cleaned on a regular maintenance schedule.


Accent Light - KLVL202 Installation Instructions

Fixture Orientation (See *Note Below)



180° Adjustability

***Note:** Swivel stem must be installed with the mounting threads facing down-to-horizontal. Fixtures may not be installed with mounting threads facing upward unless shielded from rain or sprinklers.



Additional wire and connectors may be purchased from Kim Lighting:

KLV427 #12-2 Cable KLV410 Connector
KLV432 #8-2 Cable KLV411 Connector

For warranty see: currentlighting.com/kimlighting

EC 140326006 Status A

Part No. 93049434