



**INSTRUCTIONS PERTAINING TO A RISK OF FIRE OR INJURY TO PERSONS**

**IMPORTANT SAFETY INSTRUCTIONS!**

**⚠ WARNING:** To reduce the risk of **FIRE OR INJURY TO PERSONS:** Do not overdrive fixtures with greater than 12 volts or fixture over-heating and short lamp life will occur. Do not overload the transformer by installing (or relamping) higher wattage lamps than planned. **Note:** Total wattage of all lamps connected to one transformer must not exceed the capacity of that transformer. Do not install luminaire within 10 feet (3.04m) of a pool, spa or fountain. **DO NOT** operate luminaire with missing or damaged lens.

**⚠ SAFETY WARNING:** When relamping, be sure electrical supply is **OFF**. Use discretion when touching fixture and be sure to allow fixture to cool before relamping.

**MAINTENANCE:** To maintain light efficiency and prevent fixture-overheating, glass lenses and enclosure must be kept clean and free of dirt, dust, leaves, trash (combustible materials) and mineral deposits from water. Particular care should be taken not to locate fixtures where small children can reach them if higher wattages are used.

**KEEP THIS SHEET FOR FUTURE REFERENCE.**

**Tools Required:**

- Philips Screwdriver
- Flat Blade Screwdriver
- Adjustable Wrench
- 1/8" Allen Wrench
- 3/16" Allen Wrench

**⚠** Make certain the electrical supply is **OFF** before starting fixture installation.



**1.** Remove coupling from fixture.



**2.** Tighten coupling onto mounting device.



**3.** Install fixture onto coupling. Attach fixture leads.  
**Note:** KIM KLV Mounting Options can be installed before fixture is attached.



**4.** Loosen set screw, adjust fixture rotation, and tighten set screw.

**IMPORTANT:** Do not overload the transformer by installing higher wattage fixtures than planned. Remember, the total wattage of all fixtures connected to one transformer must not exceed the capacity of that transformer.

**IMPORTANT:** When fixtures are aimed up, particular care should be taken to keep lens free of debris and mineral deposits. When fixtures are in an area where debris or mineral deposits are likely to be a problem, lower wattage lamps should be used, and lenses should be cleaned on a regular maintenance schedule.


\*Consult Kim Landscape Lighting Collection Catalog for mounting device options.

## Accent Light - KLVL206 Installation Instructions

### Fixture Orientation



**\*Note:** Swivel stem must be installed with the mounting threads facing down-to-horizontal. Fixtures may not be installed with mounting threads facing upward unless shielded from rain or sprinklers.



**5.** To adjust angle, loosen swivel screw, do not disengage. Hold fixture at desired angle and tighten swivel screw. Fixture may be aimed up or down.

**6.** Connect fixture cable to main system cable with a sealed connector.

Additional wire and connectors may be purchased from Kim Lighting:

KLV427 #12-2 Cable    KLV410 Connector  
KLV432 #8-2 Cable    KLV411 Connector

**Note:** Low voltage cable is intended for shallow burial, maximum of 6" (152 mm).

For warranty see: [currentlighting.com/kimlighting](http://currentlighting.com/kimlighting)