

LED Lamps - Tubes



Type A+B Dual Mode Lamps

Current's Type A+B Tubes offer the flexibility to be used in either Type A (ballast driven) or Type B (ballast bypass) applications. A Type A+B Tube can run off a ballast initially, and can run off mains voltage should the ballast fail, or if it is found to be incompatible. To use Type A+B lamps as Type B, the fixture must be re-wired.



PERFORMANCE HIGHLIGHTS:

Type A+B Dual Mode Lamps Light Output Range: 2000-2200 Lumens **CRI:** 80 Selectable CCT: 3000K/3500K/4000K/5000K

Efficiency: Up to 141 LPW

Wattage: 14.5W

Life: 50,000 hours L70

Temperature Rating: -20°C to 45°C

Location Rating: Damp

Fixtures: Open or Enclosed

Ballast Compatability www.LED.com/LEDTUBES-ballast-

Guide: compatibility

Certification: DLC Listed

LIMITED WARRANTY

5 years

FEATURES:

- Can be used as either Type A (ballast compatible) or Type B (ballast bypass); re-wiring required for Type B
- Type A mode allows for simple initial installation
- Type B mode allows for single-ended or double-ended power
- Double-Ended Type B mode works on shunted or unshunted
- Safety First built-in protection for installers and end users
- SpectraChoice™: color temperature levels that can be adjusted with a built-in switch, no tools required

BENEFITS:

- Simplifies stocking with Type A and Type B modes
- · Greater flexibility provides options at initial installation and in the future to rewire once ballast reaches end of life or is found to be incompatible
- Longer life and lower energy usage than linear fluorescent
- Use one lamp for many applications, simplifying project management by streamlining BOMs

LEARN MORE:

To learn more about saving money and energy, go to www.LED.com.







Do more with less.

- Reduce Inventory
- Simplify Projects
- Optimize Solutions





LED Lamps - Tubes

Type A+B Dual Mode Lamps

CUSTOMER NAME	
PROJECT NAME	
DATE	NOTES

Selectable SpectraChoice™ Dual Mode Glass Tubes - Type A+B

							TYPE A MODE						TYPE B MODE								
									Normal Bal	last Factor		ast Factor									
Bulb Shape		Lamp Watts ⁵		Description		MOL (in)		Lumens (Initial)	System Watts	Lumens (Initial)	System Watts	Lumens (Initial)	Input Voltage	Watts	Lumens (Initial)		CRI	Temp.	Rated Life L70 (Hrs) ¹	DLC [®] 4	Location Rating ³
Dual	Dual Mode 4ft Glass Tubes (Type A+B)																				
							15.5	1850	18.5	2200	26	2950	120-277	14.5	2000	>0.9	80	3000K	50,000	-	Damp
Т8	T8 G13 14.5 93319135 LED14ABT8/G4/8SC	25	48	15.5	1900	18.5	2250	26	3000	120-277	14.5	2050	>0.9	80	3500K	50,000	-	Damp			
18	GIS	14.5	93319135	LEDI4AB18/G4/85C	25	48	15.5	1900	18.5	2250	26	3000	120-277	14.5	2050	>0.9	80	4000K	50,000	-	Damp
						15.5	1850	18.5	2200	26	2950	120-277	14.5	2000	>0.9	80	5000K	50,000	-	Damp	


¹ The life rating is based on the hours of operation the lamp will provide before reaching 70% of its original lumen output (L70)


Selectable SpectraChoice™ Dual Mode Glass Tubes - Dimmer Compatability

Lamps are dimmable on 120V on the below reverse phase dimmers.

Brand	Model Number							
Compatible	Compatible Reverse Phase Dimmer List							
LUTRON	DVELV-300P-**							
LUTRON	DVELV-303P-**							
LUTRON	MAELV-600-**							

If lamp holders are shunted, follow instructions for double-ended wiring. If lamp holders are not shunted, single-ended or double-ended wiring may be used.





² Minimum order quantity = Carton Qty

³ UL 1993 Environmental Requirements for LED LAMPS

Damp Location - Exterior or interior location that is normally or periodically subject to condensation of moisture in, on, or adjacent to electrical equipment, including partially protected locations

⁴ Not all product variations on this page are DLC qualified. Visit qpl.designlights.org/solid-state-lighting to confirm qualification.

5 Bare lamp wattage operated on Normal Ballast Factor. Measured performance on Low (0.78), Normal (0.88) and High (1.18) Ballast Factors is provided for reference. Performance may vary depending on ballast model and age. Check ballast compatibility at www.LED.com/LEDTUBES-ballast-compatibility.