

CRN2-LSCS

WET LOCATION/NSF
HIGH BAY



Columbia
LIGHTING

Current 

CRN2-LSCS

WET LOCATION/NSF
HIGH BAY



Features and Benefits

- Switchable Lumen and CCT technologies maximize inventory versatility and flexibility
- 120-347V Driver
- Optional 'plug and play' occupancy sensor is easily installed into the center of the fixture
- Provides lumen packages from 15,500 to 35,040 lumens, allowing for use in a variety of applications including food processing, wash down, warehouses, gyms, garden centers and mezzanines
- Two reflector options deliver glare reduction and aesthetic customization
- Efficacy up to 162 LPW assures energy savings over traditional high bay luminaries



STOCK

Catalog Number	Part #	Color Temperature	Lumen Output Setting	Wattage	Lumen Output	LPW	Voltage
CRN2-1-LSCS-EDMV	SKU: 93167312 UPC: 840141431239	4000K	LOW	100	15800	158	120-347V
			MED	120	18600	155	
			HIGH	150	21750	145	
		5000K	LOW	100	15500	155	
			MED	120	18360	153	
			HIGH	150	21300	142	
CRN2-2-LSCS-EDMV	SKU: 93167313 UPC: 840141431246	4000K	LOW	150	24300	162	
			MED	200	30600	153	
			HIGH	240	35040	146	
		5000K	LOW	150	24000	160	
			MED	200	30200	151	
			HIGH	240	34320	143	

LSCS default setting is 5000K, HIGH lumen output

ORDERING INFORMATION

CRN2		LSCS	ED
Model	Size	Lumen Output & CCT	Dimming Voltage
CRN2 Wet Location High Bay	1 Size 1: 100/120/150W 2 Size 2: 150/200/240W	LSCS Lumen Switchable/ CCT Switchable	ED 0-10V Dimming MV 120-347V

Accessories (Optional)	Description	Part #
Safety Tether	CRN2-TLR	93130251
Wire Guard	Size 1: CRN2-1-WG	93161788
	Size 2: CRN2-2-WG	93161789
Full Wire Guard	Size 1: CRN2-1-FWG	93161790
	Size 2: CRN2-2-FWG	93161791
Polycarbonate Refractor	Size 1: CRN2-1-PC16	93161792
	Size 2: CRN2-2-PC16	93161793
Polycarbonate Drop Lens	Sizes 1 & 2: CRN2-PCL	93161794
Aluminum Reflector	Size 1: CRN2-1-AL16	93161795
	Size 2: CRN2-2-AL16	93161796
Wall Mount Bracket*	Sizes 1 & 2: CRN2-YOKE-ADPT	93130249
Snaphook	Sizes 1 & 2	93130250
PIR Occupancy Sensor	Sensor: HB03DPR	93161798
	Remote: HB03DPR-REMOTE	93161799
Emergency Battery	CRN2-ELL40	93161800



Bottom view with sensor installed