

285-B3 - TENON REDUCER

MOUNTING ACCESSORIES

DESCRIPTION

This tenon reducer fits over a round 3.0" pole to reduce from 3.5" to 2.38"

WARNING: To avoid damaging supply wiring, drill all necessary holes in poles, arms, or mounting brackets BEFORE pulling supply wires.

DIMENSIONS & WEIGHT	
Tenon Height	4.25"
Tenon Pipe ID	2.0"
Tenon Pipe OD	2.38"
Tenon Reducer ID	3.59"
Tenon Reducer OD	4.0"
Weight	6 lbs.

MOUNTING INSTRUCTIONS

- Place tenon reducer over end of pole.
- In case of missing holes on pole, drill appropriately sized holes at distances referenced in figure on the right.
- Insert bolt through tenon reducer and pole, and secure with nute.
- Install (2) set screws until contact with inner pole.

STANDARD FINISH COLORS & MATERIAL

- Steel
- Finish Powder Paint

ORDERING GUIDE

CATALOG # **Example: 285-B3-LGS**

ORDERING INFORMATION

Series	Color
285-B3 285-B3 Tenon Reducer	BLT Black Matte Textured BLS Black Gloss Smooth DBT Dark Bronze Matte Textured DBS Dark Bronze Gloss Smooth GTT Graphite Matte Textured LGS Light Grey Gloss Smooth LGT Light Grey Matte Textured PSS Platinum Silver Smooth WHT White Matte Textured WHS White Gloss Smooth VG Verde Green Textured CC Custom Color

SHIPPING PACKAGE CONTENTS	
Qty	Description
1	285-B-3 Tenon Reducer
1	3/8-16 Bolt
2	1/2-13 Set Screw
1	3/8-16 Nut
Weight	6 lbs.

